



WOYR8.E120619

Switches, Special Use Certified for Canada - Component

Enhanced searching capability for this category can be found in UL's iQ Family of Databases (iq.ul.com).

Page Bottom

Switches, Special Use Certified for Canada - Component

[See General Information for Switches, Special Use Certified for Canada - Component](#)

SWITCLAB INC
 8TH FL 66 CHUNG CHENG RD
 HSIN CHUANG
 TAIPEI HSIEN, 242 TAIWAN

E120619

Cat. No.	Amps	Volts	Hz	Load	Endurance	Temp C	POL/THR	Per Pole/Circuit Code	SPCOA
ADD; f/b 16C; f/b 4- or 6-; f/b M or A; f/b A, B, C, S or T; f/b 1- or 2-; f/b 1, 2, 3 or 4; f/b A, B, E, U or V; f/b 0 or letter; f/b letter.									
	6	24	DC	-	6K	70	1/2	-/-	-
	0.2	250	DC	-	6K				
	6	125	60	GP	6K				
	5	250	60	GP	6K				
ADD; f/b 16K; f/b 4- or 6-; f/b M or A; f/b R, S, T or C; f/b 0-; f/b 1, 2, 3 or 4; f/b letter.									
	6	24	DC	-	6K	70	1/M	-/-	-
	0.2	250	DC	-	6K				
	6	125	60	GP	6K				
	5	250	60	GP	6K				
ADP; f/b 16C; f/b 4- or 6-; f/b M or A; f/b A, B, C, S or T; f/b 1- or 2-; f/b 1, 2, 3 or 4; f/b A, B, E, U or V; f/b 0 or letter; f/b letter.									
	6	24	DC	-	6K	70	1/2	-/-	-
	0.2	250	DC	-	6K				
	6	125	60	GP	6K				
	5	250	60	GP	6K				
ADP; f/b 16K; f/b 4- or 6-; f/b M or A; f/b R, S, T or C; f/b 0-; f/b 1, 2, 3 or 4; f/b letter.									
	6	24	DC	-	6K	70	1/M	PP/-	-
	0.2	250	DC	-	6K				
	6	125	60	GP	6K				
	5	250	60	GP	6K				
D16, f/b LA, LM or PL, f/b R1, R2, R3, T1, T2, S1, S2, U1, U2, U3, V1, V2, V3 or V4, f/b 000, 1ab, 2ab, 3ab or 4ab, f/b O, A, B, C, D, E, F, G, H, J, K, L, M or N, f/b B, G, O, P, R, W or Y									
	0.2	250	DC	R	6K	55	M/M	PP/D1	2
	6	24	DC	R	6K				
	8	125	60	GP	6K				
	5	250	60	GP	6K				
D16, f/b PA or PM, f/b R1, R2, R3, T1, T2, S1, S2, U1, U2, U3, V1, V2, V3 or V4, f/b 000, 1ab, 2ab, 3ab or 4ab, f/b O, A, B, C, D, E, F, G, H, J, K, L, M or N, f/b B, G, O, P, R, W or Y									
	0.2	250	DC	R	6K	55	M/M	PP/D1	-
	6	24	DC	R	6K				
	8	125	60	GP	6K				
	5	250	60	GP	6K				


DA16S f/b numbers or letters.									
8	125	60	GP	6K	55	1/1	-/-	-	
5	250	60	GP	6K					
DH6, f/b LA, LM or PL, f/b R1, R2, R3, T1, T2, S1 or S2, f/b U1, U2, V1 or V2, f/b 000, 1ab, 2ab, 3ab, or 4ab f/b O, A, B, C, D, E, F, G, or H, f/b B, G, O, P, R, W or Y									
0.2	250	DC	R	6K	95	M/M	PP/D1	2	
6	24	DC	R	6K					
8	125	60	GP	6K					
5	250	60	GP	6K					
DH6, f/b PA or PM, f/b R1, R2, R3, T1, T2, S1 or S2, f/b U1, U2, V1 or V2, f/b 000, 1ab, 2ab, 3ab, or 4ab f/b O, A, B, C, D, E, F, G, or H, f/b B, G, O, P, R, W or Y									
0.2	250	DC	R	6K	95	M/M	PP/D1	-	
6	24	DC	R	6K					
8	125	60	GP	6K					
5	250	60	GP	6K					
P16, f/b LA or LM, f/b R1, R2, R3, S1, S2, T1 or T2, U1, U2, U3, V1, V2 or V3, f/b 1ab, f/b O, A, B, C, F, G, H, J, K, M, N, L, D or E, f/b B, G, O, Y, R or W									
6	24	DC	-	6K	55	1/2	-/-	A1	
8	125	60	GP	6K					
5	250	60	GP	6K					
PH6, f/b LA or LM; f/b R1, T1, T2, S1 or S2; f/b U1, U2, V1 or V2; f/b 1ab; f/b O, A, B, C, F, G, H, J, K, M, N, L, D or E; f/b B, G, O, P, R, W or Y									
6	24	DC	-	6K	95	1/2	-/-	-	
8	125	60	GP	6K					
5	250	60	GP	6K					

A1 - The optional printed circuit board connector used with Model P16 has not been investigated for repeated insertion or for making and breaking load current.

Note 2 - These are lighted switches employing a lamp. The lamp life should be evaluated when required by the end-use product Standard.

Marking: Markings on the switch body consist of at least items (a) and (b) or (c) as noted below (other markings shall be on the smallest shipping package):

- (a) Manufacturer's identifier (such as name or trademark, as described in the UL file)
- (b) Electrical ratings
- (c) Catalog or model number (or equivalent)
- (d) Factory code (as described in the UL Report, if more than one location)

- (e) Recognized Component Mark for Canada, 

Last Updated on 2008-12-17

[Questions?](#)

[Notice of Disclaimer](#)

[Page Top](#)

Copyright ?2009 Underwriters Laboratories Inc.®

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Listed and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Designs and/or Listings (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from Underwriters Laboratories Inc." must

appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "Copyright © 2009 Underwriters Laboratories Inc.®"

An independent organization working for a safer world with integrity, precision and knowledge.

